



---

## SETUP TIME/TEMP/DATE DISPLAY FREQUENCY (the rate at which your sign transitions between each screen).

---

1. Press **Edit** to begin editing the display frequency
2. Press **+** to increase the frequency value (the larger the number, the faster the transition)  
Press **-** to decrease the frequency value (the smaller the number, the slower the transition)
3. Press **Enter** to save the setting and exit the menu  
Press **Esc** to cancel this operation and exit the menu

---

## SETUP YOUR SIGN DISPLAY PREFERENCES (time format (12 hours or 24hours), temperature mode (Fahrenheit or Celcius) & time zone)







---

1. Press **Set** to begin editing the sign display preferences
2. Press **Line** to select time zone settings (the flashing number should be 0)








### Display number 0 = time zone settings

1. Press **+** to display Eastern Time
2. Press **-** to display Pacific Time
3. Press **Enter** to save the setting and exit the menu
4. Press **Esc** to cancel this operation and exit the menu

## Display number 1 = temperature format (Celsius or Fahrenheit)

1. Press  to begin editing the sign display preferences
2. Press  2 times to switch to temperature (the flashing number should be 1)
  1. Press  to display Fahrenheit
  2. Press  to display Celsius
3. Press  to save the setting and exit the menu
4. Press  to cancel this operation and exit the menu

## Display number 2 = time format (12 hour or 24 hour)

1. Press  to begin editing the sign display preferences
2. Press  3 times to switch to temperature (the flashing number should be 2)
  1. Press  to display 12 hour time format \* In 12 hour format  
press  to switch between A.M. and P.M.
  2. Press  to display 24 hour time format
3. Press  to save the setting and exit the menu
4. Press  to cancel this operation and exit the menu







---

## SETUP AUTO AND MANUAL SCREEN DIMMING (changes the screen brightness settings)

---

1. Press  to begin editing the sign display preferences
2. Press  4 times to switch to temperature (the flashing number should be 3)








### Display number 3 = manual/auto dimming

1. Press  to setup auto dimming  
press  to setup manual dimming
2. Press  to increase brightness (larger numbers are brighter)
3. Press  to decrease brightness (smaller numbers are dimmer)
4. Press  to save the setting and exit the menu
5. Press  to cancel this operation and exit the menu

---

## CHANGE YOUR DISPLAY TIME SETTINGS











---

1. Press  to start time setup (the selected digit will begin flashing)
2. Press  to increase selected time
3. Press  to decrease selected time
4. Press  to select one digit to the right
3. Press  to select one digit to the left
3. Press  to save the setting and exit the menu
4. Press  to cancel this operation and exit the menu

---

## CHANGE YOUR DISPLAY DATE SETTINGS


---


1. Press  +  to setup the year (the selected digit will begin flashing)  
Press  +  to setup the date (the selected digit will begin flashing)
2. Press  to increase selected digit
3. Press  to decrease selected digit
4. Press  to select one digit to the right
3. Press  to select one digit to the left
3. Press  to save the setting and exit the menu
4. Press  to cancel this operation and exit the menu

---



## TOGGLE ON/OFF TIME, TEMPERATURE AND DATE

---



1. Press  to go into soft-off mode, then press  to begin setup

2. Press  to select a function to toggle on/off





### Number 0 = time

2. Press  to toggle off, press  to toggle on

### Number 1 = temperature

2. Press  to toggle off, press  to toggle on



### Number 1 = date


2. Press  to toggle off, press  to toggle on
3. Press  to save the setting and exit the menu
4. Press  to cancel this operation and exit the menu

---



## TOGGLE ON/OFF TIME, TEMPERATURE AND DATE

---



1. Press  to go into soft-off mode, then press  to begin setup

2. Press  to select a function to toggle on/off



### **Number 0 = time**


2. Press  to toggle off, press  to toggle on


### **Number 1 = temperature**

2. Press  to toggle off, press  to toggle on

### **Number 1 = date**

2. Press  to toggle off, press  to toggle on

3. Press  to save the setting and exit the menu

4. Press  to cancel this operation and exit the menu